

## L83-CZK6

### L83 DIP SWITCHES SETTING : 1

Supported bill Kč 100, 200, 500, 1000, 2000, 5000 6bills.  
With stacker : Kč 100, 200, 500, 1000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Kč 50	OFF	OFF	OFF							
	2 Pulse / Kč 50	OFF	OFF	ON							
	3 Pulse / Kč 50	OFF	ON	OFF							
	4 Pulse / Kč 50	OFF	ON	ON							
	5 Pulse / Kč 50	ON	OFF	OFF							
	10 Pulse / Kč 50	ON	OFF	ON							
	20 Pulse / Kč 50	ON	ON	OFF							
	100 Pulse / Kč 50	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Kč 100						ON				
	Reject Kč 100						OFF				
★	Accept Kč 200 & 500							ON			
	Reject Kč 200 & 500							OFF			
★	Accept Kč 1000								ON		
	Reject Kč 1000								OFF		
★	Accept Kč 2000									ON	
	Reject Kč 2000									OFF	
★	Accept Kč 5000										ON
	Reject Kč 5000										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## L83-CZK6(Pulse/ccTalk/Smiley Parallel)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	Smiley Parallel Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	CRC 16-bit checksum	ON			
	8-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	cctalk Interface		OFF	OFF	
	Smiley Parallel Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

### DIP SWITCHES SETTING : 2(Smiley Parallel)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	cctalk Interface		OFF	OFF	
★	Smiley Parallel Mode		ON	ON	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	ccTalk	Smiley Parallel
BV1			
BV2	Kč 100	Kč 100	Kč 100
BV3	Kč 200	Kč 200	Kč 200
BV4	Kč 500	Kč 500	Kč 500
BV5	Kč 1000	Kč 1000	Kč 1000
BV6	Kč 2000	Kč 2000	Kč 2000
BV7	Kč 5000	Kč 5000	Kč 5000