

L83-CZK6

L83/P3/P6 DIP SWITCHES SETTING : 1(ICT104U/MDB/RS232 A0)

Supported bill CZK 100, 200, 500, 1000, 2000, 5000 6bills.
With stacker bill CZK 100, 200, 500, 1000 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
Reserved	ON									
★ Reserved	OFF									
Reserved		ON								
★ Reserved		OFF								
Reserved			ON							
★ Reserved			OFF							
Reserved				ON						
★ Reserved				OFF						
Reserved					ON					
★ Reserved					OFF					
★ Accept CZK 100						ON				
Reject CZK 100						OFF				
★ Accept CZK 200 & 500							ON			
Reject CZK 200 & 500							OFF			
★ Accept CZK 1000								ON		
Reject CZK 1000								OFF		
★ Accept CZK 2000									ON	
Reject CZK 2000									OFF	
★ Accept CZK 5000										ON
Reject CZK 5000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

Currency Assign Data

Interface Bill value	MDB	RS232 A0	ICT104U
BV1			
BV2	CZK 100	CZK 100	CZK 100
BV3	CZK 200	CZK 200	CZK 200
BV4	CZK 500	CZK 500	CZK 500

Interface Bill value	MDB	RS232 A0	ICT104U
BV5	CZK 1000	CZK 1000	CZK 1000
BV6	CZK 2000	CZK 2000	CZK 2000
BV7	CZK 5000	CZK 5000	CZK 5000

L83-CZK6(ICT104U/MDB/RS232 A0)

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
MDB Mode		ON	ON	
RS232 A0 Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
★ MDB Mode		ON	ON	
RS232 A0 Mode		ON	OFF	
ICT104U Interface		OFF	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4	RS232 A0 INFORMATION BillType Data
★ Reserved	ON				
	OFF				1 Reserved
MDB Mode		ON	ON		2 CZK 100
★ RS232 A0 Mode		ON	OFF		3 CZK 200
ICT104U Interface		OFF	ON		4 CZK 500
Reserved		OFF	OFF		5 CZK 1000
★ Reserved				ON	6 CZK 2000
				OFF	7 CZK 5000
					8 Reserved

★ Manufacture setting