

L83-CZK6

L83-P3/P6 DIP SWITCHES SETTING : 1(ccTalk/RS232 A0/RS232 A1)

Supported bill CZK 100, 200, 500, 1000, 2000, 5000 6bills.

With stacker bill CZK 100, 200, 500, 1000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reserve	ON									
		OFF									
★	Reserve		ON								
			OFF								
★	Reserve			ON							
				OFF							
★	Reserve				ON						
					OFF						
★	Reserve					ON					
						OFF					
★	Accept CZK 100						ON				
★	Reject CZK 100						OFF				
★	Accept CZK 200 & 500							ON			
	Reject CZK 200 & 500							OFF			
★	Accept CZK 1000								ON		
	Reject CZK 1000								OFF		
★	Accept CZK 2000									ON	
	Reject CZK 2000									OFF	
★	Accept CZK 5000										ON
	Reject CZK 5000										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-CZK6(ccTalk/RS232 A0/RS232 A1)

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	ccTalk	OFF	OFF		
	RS232 A0	ON	OFF		
	RS232 A1	OFF	ON		
	Reserved	ON	ON		
★	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)			ON	
	ccTalk Interface			OFF	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	ccTalk	OFF	OFF		
	RS232 A0	ON	OFF		
	RS232 A1	OFF	ON		
	Reserved	ON	ON		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	CZK 100
3	CZK 200
4	CZK 500
5	CZK 1000
6	CZK 2000
7	CZK 5000
8	Reserved

DIP SWITCHES SETTING : 2(RS232 A1)

	FUNCTION	SW1	SW2	SW3	SW4
★	ccTalk	OFF	OFF		
	RS232 A0	ON	OFF		
★	RS232 A1	OFF	ON		
	Reserved	ON	ON		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	RS232 A0	RS232 A1	ccTalk
BV1			
BV2	CZK 100	CZK 100	CZK 100
BV3	CZK 200	CZK 200	CZK 200
BV4	CZK 500	CZK 500	CZK 500
BV5	CZK 1000	CZK 1000	CZK 1000
BV6	CZK 2000	CZK 2000	CZK 2000
BV7	CZK 5000	CZK 5000	CZK 5000