

L83-EUR7

L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB)

Supported bill EUR 5, 10, 20, 50, 100, 200, 500 7 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★ 1 Pulse / EUR 5	OFF	OFF	OFF								
2 Pulse / EUR 5	OFF	OFF	ON								
3 Pulse / EUR 5	OFF	ON	OFF								
4 Pulse / EUR 5	OFF	ON	ON								
5 Pulse / EUR 5	ON	OFF	OFF								
10 Pulse / EUR 5	ON	OFF	ON								
20 Pulse / EUR 5	ON	ON	OFF								
100 Pulse / EUR 5	ON	ON	ON								
Fast output Pulse Lo= 50ms Hi=100ms											ON
★ Slow output Pulse Lo= 50ms Hi=300ms											OFF
Inhibit level Active Low					ON						
★ Inhibit level Active High					OFF						
★ Accept EUR 5 & 10						ON					
Reject EUR 5 & 10						OFF					
★ Accept EUR 20 & 50							ON				
Reject EUR 20 & 50							OFF				
★ Accept EUR 100								ON			
Reject EUR 100								OFF			
★ Accept EUR 200 & 500									ON		
Reject EUR 200 & 500									OFF		
★ Accept Normal										ON	
Reject EUR 5(2002) & 10(2002)										OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L83-EUR7(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4	
★ Pulse Normal High	ON				
Pulse Normal Low	OFF				
★ Pulse Mode		ON	OFF		
ICT104U Interface		OFF	ON		
MDB Mode		ON	ON		
Reserved		OFF	OFF		
Reserved					ON
					OFF

★ Manufacture setting

Interface Bill value	Pulse	ICT104U	MDB
BV1	EUR 5	EUR 5	EUR 5
BV2	EUR 10	EUR 10	EUR 10
BV3	EUR 20	EUR 20	EUR 20
BV4	EUR 50	EUR 50	EUR 50
BV5	EUR 100	EUR 100	EUR 100
BV6	EUR 200	EUR 200	EUR 200
BV7	EUR 500	EUR 500	EUR 500

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
Reserved				
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
★ MDB Mode		ON	ON	
Reserved		OFF	OFF	
Reserved				
				OFF

★ Manufacture setting