

L83-PLN6

L83 Option Switch Settings : 1(Pulse/RS232 A0/ccTalk/Parallel A5)

Supported bill PLN 10, 20, 50, 100, 200, 500 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / PLN 10	OFF	OFF	OFF							
	2 Pulses / PLN 10	OFF	OFF	ON							
	3 Pulses / PLN 10	OFF	ON	OFF							
	4 Pulses / PLN 10	OFF	ON	ON							
	5 Pulses / PLN 10	ON	OFF	OFF							
	10 Pulses / PLN 10	ON	OFF	ON							
	20 Pulses / PLN 10	ON	ON	OFF							
	100 Pulses / PLN 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept PLN 10 & 20						ON				
	Reject PLN 10 & 20						OFF				
★	Accept PLN 50							ON			
	Reject PLN 50							OFF			
★	Accept PLN 100								ON		
	Reject PLN 100								OFF		
★	Accept PLN 200									ON	
	Reject PLN 200									OFF	
★	Accept PLN 500										ON
	Reject PLN 500										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccTalk	Parallel A5	Interface Bill value	Pulse	RS232 A0	ccTalk	Parallel A5
BV1	PLN 10	PLN 10	PLN 10	PLN 10	BV4	PLN 100	PLN 100	PLN 100	PLN 100
BV2	PLN 20	PLN 20	PLN 20	PLN 20	BV5	PLN 200	PLN 200	PLN 200	PLN 200
BV3	PLN 50	PLN 50	PLN 50	PLN 50	BV6	PLN 500	PLN 500	PLN 500	PLN 500

L83-PLN6(Pulse/RS232 A0/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	RS232 A0 Mode		ON	ON	OFF
★	Pulse Mode		ON	OFF	OFF
	Parallel A5 Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A5)

	FUNCTION	SW1	SW2	SW3	SW4
★	Four-denominations mode (Note.4)	ON			
	Binary mode	OFF			
	RS232 A0 Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
★	Parallel A5 Mode		ON	OFF	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
★	RS232 A0 Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
	Parallel A5 Mode		ON	OFF	ON

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	PLN 10
2	PLN 20
3	PLN 50
4	PLN 100
5	PLN 200
6	PLN 500

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
★	ccTalk Mode		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note.3 Turn this dip to with restart the bill acceptor will restore

ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.4 4 denominations mode, reject PLN 200 & PLN 500.