

# L83-RSD8

## L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U/RS232 A0)

Supported bill RSD 10, 20, 50, 100, 200, 500, 1000, 2000 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★ 1 Pulse / RSD 10	OFF	OFF	OFF								
2 Pulses / RSD 10	OFF	OFF	ON								
3 Pulses / RSD 10	OFF	ON	OFF								
4 Pulses / RSD 10	OFF	ON	ON								
5 Pulses / RSD 10	ON	OFF	OFF								
10 Pulses / RSD 10	ON	OFF	ON								
20 Pulses / RSD 10	ON	ON	OFF								
100 Pulses / RSD 10	ON	ON	ON								
Fast output Pulse Lo= 50ms Hi=100ms											ON
★ Slow output Pulse Lo= 50ms Hi=300ms											OFF
Inhibit level Active Low					ON						
★ Inhibit level Active High					OFF						
★ Accept RSD 10 & 20						ON					
Reject RSD 10 & 20						OFF					
★ Accept RSD 50 & 100							ON				
Reject RSD 50 & 100							OFF				
★ Accept RSD 200 & 500								ON			
Reject RSD 200 & 500								OFF			
★ Accept RSD 1000									ON		
Reject RSD 1000									OFF		
★ Accept RSD 2000										ON	
Reject RSD 2000										OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse mode.

# L83-RSD8(Pulse/ICT104U/RS232 A0)

## DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
RS232 A0 Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

Interface Bill value	Pulse	RS232 A0	ICT104U
BV1	RSD 10	RSD 10	RSD 10
BV2	RSD 20	RSD 20	RSD 20
BV3	RSD 50	RSD 50	RSD 50
BV4	RSD 100	RSD 100	RSD 100
BV5	RSD 200	RSD 200	RSD 200
BV6	RSD 500	RSD 500	RSD 500
BV7	RSD 1000	RSD 1000	RSD 1000
BV8	RSD 2000	RSD 2000	RSD 2000

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
RS232 A0 Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
RS232 A0 Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

RS232 A0 INFORMATION	
BillType Data	
Code	Denomination
1	RSD 10
2	RSD 20
3	RSD 50
4	RSD 100
5	RSD 200
6	RSD 500
7	RSD 1000
8	Reserved
9	RSD 2000