

L83-SBD6

L83 Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill SBD 5, 10, 20, 40, 50, 100 6bills.

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ 1 Pulse / SBD 5 | OFF | OFF | OFF | | | | | | | |
| 2 Pulses / SBD 5 | OFF | OFF | ON | | | | | | | |
| 3 Pulses / SBD 5 | OFF | ON | OFF | | | | | | | |
| 4 Pulses / SBD 5 | OFF | ON | ON | | | | | | | |
| 5 Pulses / SBD 5 | ON | OFF | OFF | | | | | | | |
| 10 Pulses / SBD 5 | ON | OFF | ON | | | | | | | |
| 20 Pulses / SBD 5 | ON | ON | OFF | | | | | | | |
| 100 Pulses / SBD 5 | ON | ON | ON | | | | | | | |
| Fast output Pulse <small>Lo= 50ms Hi=100ms</small> | | | | ON | | | | | | |
| ★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small> | | | | OFF | | | | | | |
| Inhibit level Active Low | | | | | ON | | | | | |
| Inhibit level Active High | | | | | OFF | | | | | |
| ★ Accept SBD 5 & 10 & 20 | | | | | | ON | | | | |
| Reject SBD 5 & 10 & 20 | | | | | | OFF | | | | |
| ★ Accept SBD 40 | | | | | | | ON | | | |
| Reject SBD 40 | | | | | | | OFF | | | |
| ★ Accept SBD 50 | | | | | | | | ON | | |
| Reject SBD 50 | | | | | | | | OFF | | |
| ★ Accept SBD 100 | | | | | | | | | ON | |
| Reject SBD 100 | | | | | | | | | OFF | |
| Simulation BillBox Has Been Removed | | | | | | | | | | ON |
| ★ Default | | | | | | | | | | OFF |

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

Currency Assign Data

| Interface Bill value | RS232 A0 | Pulse | ccNet | ICT104U |
|-------------------------|----------|--------|--------|---------|
| BV1 | SBD 5 | SBD 5 | SBD 5 | SBD 5 |
| BV2 | SBD 10 | SBD 10 | SBD 10 | SBD 10 |
| BV3 | SBD 20 | SBD 20 | SBD 20 | SBD 20 |
| BV4 | SBD 50 | SBD 40 | SBD 40 | SBD 40 |

| Interface Bill value | RS232 A0 | Pulse | ccNet | ICT104U |
|-------------------------|----------|---------|---------|---------|
| BV5 | SBD 100 | SBD 50 | SBD 50 | SBD 50 |
| BV6 | SBD 40 | SBD 100 | SBD 100 | SBD 100 |

L83-SBD6(Pulse/RS232 A0/ccNet/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|----------------------------|-----|-----|-----|-----|
| ★ Credit-Pulse Normal High | ON | | | |
| Credit-Pulse Normal Low | OFF | | | |
| RS232 A0 Mode | | ON | ON | |
| ★ Pulse Mode | | ON | OFF | |
| ccNet Mode | | OFF | OFF | |
| ICT104U Mode | | OFF | ON | |
| Reserved | | | | ON |
| ★ Reserved | | | | OFF |

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|-----------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| Reserved | OFF | | | |
| ★ RS232 A0 Mode | | ON | ON | |
| Pulse Mode | | ON | OFF | |
| ccNet Mode | | OFF | OFF | |
| ICT104U Mode | | OFF | ON | |
| Reserved | | | | ON |
| ★ Reserved | | | | OFF |

RS232 A0 INFORMATION

| BillType Data | |
|---------------|--------------|
| Code | Denomination |
| 1 | Reserved |
| 2 | Reserved |
| 3 | \$A 5 |
| 4 | \$A 10 |
| 5 | \$A 20 |
| 6 | \$A 50 |
| 7 | \$A 100 |
| 8 | \$A 40 |

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccNet)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|------------------|-----|-----|-----|-----|
| Baud rate 19200 | ON | | | |
| ★ Baud rate 9600 | OFF | | | |
| RS232 A0 Mode | | ON | ON | |
| Pulse Mode | | ON | OFF | |
| ★ ccNet Mode | | OFF | OFF | |
| ICT104U Mode | | OFF | ON | |
| Reserved | | | | ON |
| ★ Reserved | | | | OFF |

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| Reserved | ON | | | |
| ★ Reserved | OFF | | | |
| RS232 A0 Mode | | ON | ON | |
| Pulse Mode | | ON | OFF | |
| ccNet Mode | | OFF | OFF | |
| ★ ICT104U Mode | | OFF | ON | |
| Reserved | | | | ON |
| ★ Reserved | | | | OFF |

★ Manufacture setting