

S7A II-EUR3 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill € 5, 10, 20 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject € 5	ON											
★	Accept € 5	OFF											
★	Reject € 10		ON										
★	Accept € 10		OFF										
★	Reject € 20			ON									
★	Accept € 20			OFF									
★	High Acceptance				ON								
★	High Security				OFF								
★	Enable, if fishing, BA doesn't work any more					ON							
★	Disable, BA works normally					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Stack Banknote when Power-up							ON					
★	Reject Banknote when Power-up							OFF					
★	Other Interface	Test Mode (No Communication)							ON				
★		Operation Mode							OFF				
★	Pulse Mode	Inhibit Active HIGH (Test)							ON				
★		Inhibit Active LOW							OFF				
★	ENABLE IrDA Download								ON				
★	Reserved								OFF				
★	Reserved									ON			
★	Reserved									OFF			
★	Reserved										ON		
★	Reserved										OFF		
★	Reserved											ON	
★	Reserved											OFF	

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

S7A II-EUR3(Pulse/MDB/ICT104U/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / € 5 (Note3)			OFF	OFF
	5 pulses / € 5 (Note3)			OFF	ON
	10 pulses / € 5 (Note3)			ON	OFF
	25 pulses / € 5 (Note3)			ON	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(Other)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	Parallel A3
BV1	€ 5	€ 5	€ 5	€ 5
BV2	€ 10	€ 10	€ 10	€ 10
BV3	€ 20	€ 20	€ 20	€ 20