

S7A II-NZD4 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill NZD 5, 10, 20, 50 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	
★	Reject NZD 5	ON												
	Accept NZD 5	OFF												
★	Reject NZD 10		ON											
	Accept NZD 10		OFF											
★	Reject NZD 20			ON										
	Accept NZD 20			OFF										
★	Reject NZD 50				ON									
	Accept NZD 50				OFF									
★	Enable, if fishing, BA doesn't work any more					ON								
	Disable, BA works normally					OFF								
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON							
	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF							
★	Stack Banknote when Power-up							ON						
	Reject Banknote when Power-up							OFF						
★	Other Interface	Test Mode (No Communication)							ON					
		Operation Mode							OFF					
★	Pulse Mode	Inhibit Active HIGH (Test)							ON					
		Inhibit Active LOW							OFF					
★	ENABLE IrDA Download									ON				
	Reserved									OFF				
★	ENABLE INHIBIT-Sleep Only											ON		
	5 second Timeout Only											OFF		
★	NORMAL												OFF	OFF
	MODE1												OFF	ON
	MODE2												ON	OFF
	MODE1+2												ON	ON

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note:

NORMAL: No sleep function

MODE 1: Bill-acceptor wakes up VMC with banknote only (special cable required)

MODE 2: VMC wakes up bill-acceptor

MODE 1+2: Bill-acceptor wakes up with banknote or by VMC

S7A II-NZD4(Pulse/MDB/ICT104U/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / NZD 5			OFF	OFF
	2 pulses / NZD 5			OFF	ON
	10 pulses / NZD 5			ON	OFF
	20 pulses / NZD 5			ON	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A3)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
★	Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	Parallel A3
BV1	NZD 5	NZD 5	NZD 5	NZD 5
BV2	NZD 10	NZD 10	NZD 10	NZD 10
BV3	NZD 20	NZD 20	NZD 20	NZD 20
BV4	NZD 50	NZD 50	NZD 50	NZD 50