

S7ER-IDR6 Option Switch Settings: (Pulse)

Supported bill Rp 2000, 5000, 10000, 20000, 50000, 100000 6bills.

S7ER dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★	Reject Rp 2000	ON															
★	Accept Rp 2000	OFF															
	Reject Rp 5000		ON														
★	Accept Rp 5000		OFF														
	Reject Rp 10000 & 20000			ON													
★	Accept Rp 10000 & 20000			OFF													
	Reject Rp 50000				ON												
★	Accept Rp 50000				OFF												
	Reject Rp 100000					ON											
★	Accept Rp 100000					OFF											
	High Security					ON											
★	High Acceptance					OFF											
	Reserve						ON										
★	Reserve						OFF										
	Inhibit Active HIGH							ON									
★	Inhibit Active LOW							OFF									
	Pulse Speed	100ms LO / 100ms HI							ON								
★		50ms LO / 50ms HI							OFF								
	Reserve									ON							
★										OFF							
	Reserve										ON						
★											OFF						
	Reserve											ON					
★												OFF					
	Credit-Pulse Normal HIGH												ON				
★	Credit-Pulse Normal LOW												OFF				
	Pulse Mode													ON			
★	ICT104U Mode													OFF			
	1 pulse / Rp 1000														OFF	OFF	
★	5 pulses / Rp 1000														OFF	ON	
	10 pulses / Rp 1000														ON	OFF	
★	25 pulses / Rp 1000														ON	ON	

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. High Security mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

S7ER-IDR6 (ICT104U)

S7ER dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★	Reject Rp 2000	ON															
	Accept Rp 2000	OFF															
★	Reject Rp 5000		ON														
	Accept Rp 5000		OFF														
★	Reject Rp 10000 & 20000			ON													
	Accept Rp 10000 & 20000			OFF													
★	Reject Rp 50000				ON												
	Accept Rp 50000				OFF												
★	Reject Rp 100000					ON											
	Accept Rp 100000					OFF											
★	High Security						ON										
	High Acceptance						OFF										
★	Reserved							ON									
	Reserved							OFF									
★	Test Mode								ON								
	Reserved								OFF								
★	Reserved									ON							
	Reserved									OFF							
★	Reserved										ON						
	Reserved										OFF						
★	Reserved											ON					
	Reserved											OFF					
★	Pulse Mode												ON				
	ICT104U Mode													OFF			
★	Reserved														ON		
	Reserved															OFF	
★	Reserved																ON
	Reserved																OFF

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. High Security mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Currency Assign Data

Interface Bill value	ICT104U	Pulse	Interface Bill value	ICT104U	Pulse
BV1			BV5	Rp 20000	Rp 20000
BV2	Rp 2000	Rp 2000	BV6	Rp 50000	Rp 50000
BV3	Rp 5000	Rp 5000	BV7	Rp 100000	Rp 100000
BV4	Rp 10000	Rp 10000			