

S7ER-IDR7 Option Switch Settings: (Pulse)

Supported bill Rp 1000, 2000, 5000, 10000, 20000, 50000, 100000
7 bills.

S7ER dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★	Reject Rp 1000 & 2000	ON															
★	Accept Rp 1000 & 2000	OFF															
★	Reject Rp 5000 & 10000		ON														
★	Accept Rp 5000 & 10000		OFF														
★	Reject Rp 20000			ON													
★	Accept Rp 20000			OFF													
★	Reject Rp 50000				ON												
★	Accept Rp 50000				OFF												
★	Reject Rp 100000					ON											
★	Accept Rp 100000					OFF											
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★	Stack Banknote when Power-up							ON									
★	Reject Banknote when Power-up							OFF									
★	Inhibit Active HIGH								ON								
★	Inhibit Active LOW								OFF								
★	Pulse Speed		100ms LO / 100ms HI						ON								
★			50ms LO / 50ms HI						OFF								
★	Reserve									ON							
★										OFF							
★	Normal										OFF	OFF					
★	Mode 1											OFF	ON				
★	Mode 2											ON	OFF				
★	Mode 1 + 2											ON	ON				
★	Credit-Pulse Normal HIGH												ON				
★	Credit-Pulse Normal LOW												OFF				
★	Pulse Mode													ON			
★	ICT Mode													OFF			
★	1 pulse / Rp 1000														OFF	OFF	
★	5 pulses / Rp 1000															OFF	ON
★	10 pulses / Rp 1000															ON	OFF
★	25 pulses / Rp 1000															ON	ON

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.

3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

4. Mode 2 : VMC wakes up bill-acceptor.

5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.

Appendix

S7ER-IDR7 (ICT106S)

S7ER dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★	Reject Rp 1000 & 2000	ON															
★	Accept Rp 1000 & 2000	OFF															
★	Reject Rp 5000 & 10000		ON														
★	Accept Rp 5000 & 10000		OFF														
★	Reject Rp 20000			ON													
★	Accept Rp 20000			OFF													
★	Reject Rp 50000				ON												
★	Accept Rp 50000				OFF												
★	Reject Rp 100000					ON											
★	Accept Rp 100000					OFF											
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★	Stack Banknote when Power-up							ON									
★	Reject Banknote when Power-up							OFF									
★	Test Mode								ON								
★	Reserved								OFF								
★	Pulse Speed		100ms LO / 100ms HI						ON								
★			50ms LO / 50ms HI						OFF								
★	Reserved									ON							
★										OFF							
★	Normal											OFF	OFF				
★	Mode 1											OFF	ON				
★	Mode 2											ON	OFF				
★	Mode 1 + 2											ON	ON				
★	Reserved													ON			
★	Reserved													OFF			
★	Pulse Mode														ON		
★	ICT Mode														OFF		
★	Reserved															ON	
★	Reserved															OFF	
★	Reserved																ON
★	Reserved																OFF

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Currency Assign Data

Interface Bill Value	ICT	Pulse
BV1	Rp 1000	Rp 1000
BV2	Rp 2000	Rp 2000
BV3	Rp 5000	Rp 5000
BV4	Rp 10000	Rp 10000
BV5	Rp 20000	Rp 20000
BV6	Rp 50000	Rp 50000
BV7	Rp 100000	Rp 100000