

S7ER-ZAR5 Option Switch Settings: (Pulse)

Supported bill ZAR 10, 20, 50, 100, 200 5bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject ZAR 10	ON															
★ Accept ZAR 10	OFF															
Reject ZAR 20		ON														
★ Accept ZAR 20		OFF														
Reject ZAR 50			ON													
★ Accept ZAR 50			OFF													
Reject ZAR 100				ON												
★ Accept ZAR 100				OFF												
Reject ZAR 200					ON											
★ Accept ZAR 200					OFF											
Disable Bill Reject 4 Times BA Stop By 30 Sec					ON											
★ Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF											
Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
Inhibit Active HIGH								ON								
★ Inhibit Active LOW								OFF								
Pulse Speed	100ms HI / 100ms LO							ON								
★	50ms HI / 50ms LO							OFF								
ENABLE INHIBIT-Sleep only									ON							
★ 5 second Timeout only									OFF							
Normal										OFF	OFF					
Mode 1										OFF	ON					
Mode 2										ON	OFF					
★ Mode 1 + 2										ON	ON					
★ Credit-Pulse Normal HIGH Enable Optical anti-stringing design												ON				
Credit-Pulse Normal LOW Disable Optical anti-stringing design												OFF				
★ Pulse Mode													ON			
ICT106S Mode													OFF			
★ 1 pulse / ZAR 10														OFF	OFF	
5 pulses / ZAR 10															OFF	ON
10 pulses / ZAR 10														ON		OFF
25 pulses / ZAR 10														ON		ON

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.

3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

4. Mode 2 : VMC wakes up bill-acceptor.

5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.

Currency Assign Data

Interface Bill value	ICT106S	Pulse
BV1	10	10
BV2	20	20
BV3	50	50
BV4	100	100
BV5	200	200

S7ER-ZAR5 (ICT106S)

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject ZAR 10	ON															
★ Accept ZAR 10	OFF															
Reject ZAR 20		ON														
★ Accept ZAR 20		OFF														
Reject ZAR 50			ON													
★ Accept ZAR 50			OFF													
Reject ZAR 100				ON												
★ Accept ZAR 100				OFF												
Reject ZAR 200					ON											
★ Accept ZAR 200					OFF											
Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
Test Mode								ON								
★ Reserved								OFF								
Reserve									ON							
★ Reserve									OFF							
ENABLE INHIBIT-Sleep only										ON						
★ 5 second Timeout only										OFF						
Normal											OFF	OFF				
Mode 1											OFF	ON				
Mode 2											ON	OFF				
★ Mode 1 + 2											ON	ON				
ENABLE Optical anti-stringing design													ON			
★ DISABLE Optical anti-stringing design													OFF			
Pulse Mode														ON		
★ ICT106 Mode														OFF		
★ Reserved															OFF	OFF
Reserved															OFF	ON
Reserved															ON	OFF
Reserved															ON	ON

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.

3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

4. Mode 2 : VMC wakes up bill-acceptor.

5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.