

## V7P-AUD5

### V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill AUD 5, 10, 20, 50, 100 5bills.

V7P dip-switch settings and functions:

| FUNCTION                      | SW1 | SW2                 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|-------------------------------|-----|---------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject AUD 5                | ON  |                     |     |     |     |     |     |     |     |     |     |     |
| ★ Accept AUD 5                | OFF |                     |     |     |     |     |     |     |     |     |     |     |
| ★ Reject AUD 10               |     | ON                  |     |     |     |     |     |     |     |     |     |     |
| ★ Accept AUD 10               |     | OFF                 |     |     |     |     |     |     |     |     |     |     |
| ★ Reject AUD 20               |     |                     | ON  |     |     |     |     |     |     |     |     |     |
| ★ Accept AUD 20               |     |                     | OFF |     |     |     |     |     |     |     |     |     |
| ★ Reject AUD 50               |     |                     |     | ON  |     |     |     |     |     |     |     |     |
| ★ Accept AUD 50               |     |                     |     | OFF |     |     |     |     |     |     |     |     |
| ★ Reject AUD 100              |     |                     |     |     | ON  |     |     |     |     |     |     |     |
| ★ Accept AUD 100              |     |                     |     |     | OFF |     |     |     |     |     |     |     |
| ★ Reserved                    |     |                     |     |     | ON  |     |     |     |     |     |     |     |
| ★ Reserved                    |     |                     |     |     | OFF |     |     |     |     |     |     |     |
| ★ Harness Disable             |     |                     |     |     |     | ON  |     |     |     |     |     |     |
| ★ Harness Enable              |     |                     |     |     |     | OFF |     |     |     |     |     |     |
| ★ Inhibit Active High         |     |                     |     |     |     |     | ON  |     |     |     |     |     |
| ★ Inhibit Active Low          |     |                     |     |     |     |     | OFF |     |     |     |     |     |
| ★ 1 pulse / AUD 5             |     |                     |     |     |     |     |     | OFF | OFF |     |     |     |
| 5 pulses / AUD 5              |     |                     |     |     |     |     |     | ON  | OFF |     |     |     |
| 10 pulses / AUD 5             |     |                     |     |     |     |     |     | OFF | ON  |     |     |     |
| 25 pulses / AUD 5             |     |                     |     |     |     |     |     | ON  | ON  |     |     |     |
| ★ Interface Timing Conversion |     | 50ms LO / 50ms HI   |     |     |     |     |     |     |     | OFF | OFF |     |
|                               |     | 60ms LO / 300ms HI  |     |     |     |     |     |     |     | ON  | OFF |     |
|                               |     | 30ms LO / 50ms HI   |     |     |     |     |     |     |     | OFF | ON  |     |
|                               |     | 150ms LO / 150ms HI |     |     |     |     |     |     |     | ON  | ON  |     |

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

## V7P-AUD5(Pulse/ICT104V/ICT104U/MDB)

### Interface Settings: 2(Pulse) Currency Assign Data

| INTERFACE                  | SW1 | SW2 | SW3 | SW4 |
|----------------------------|-----|-----|-----|-----|
| ★ Credit-Pulse Normal HIGH | ON  |     |     |     |
| Credit-Pulse Normal LOW    | OFF |     |     |     |
| ★ Pulse Mode               |     | ON  | OFF |     |
| ICT104U Mode               |     | OFF | OFF |     |
| ICT104V Mode               |     | OFF | ON  |     |
| MDB Mode                   |     | ON  | ON  |     |
| ★ Reserved                 |     |     |     | ON  |
|                            |     |     |     | OFF |

★ Manufacture setting

| Interface Bill value | ICT104U | ICT104V | Pulse   | MDB     |
|----------------------|---------|---------|---------|---------|
| BV1                  | AUD 5   | AUD 5   | AUD 5   | AUD 5   |
| BV2                  | AUD 10  | AUD 10  | AUD 10  | AUD 10  |
| BV3                  | AUD 20  | AUD 20  | AUD 20  | AUD 20  |
| BV4                  | AUD 50  | AUD 50  | AUD 50  | AUD 50  |
| BV5                  | AUD 100 | AUD 100 | AUD 100 | AUD 100 |

### Interface Settings: 2(ICT104U/ICT104V)

| INTERFACE      | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| ★ Reserved     | ON  |     |     |     |
| Reserved       | OFF |     |     |     |
| Pulse Mode     |     | ON  | OFF |     |
| ★ ICT104U Mode |     | OFF | OFF |     |
| ICT104V Mode   |     | OFF | ON  |     |
| MDB Mode       |     | ON  | ON  |     |
| ★ Reserved     |     |     |     | ON  |
|                |     |     |     | OFF |

★ Manufacture setting

| INTERFACE      | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| ★ Reserved     | ON  |     |     |     |
| Reserved       | OFF |     |     |     |
| Pulse Mode     |     | ON  | OFF |     |
| ★ ICT104U Mode |     | OFF | OFF |     |
| ICT104V Mode   |     | OFF | ON  |     |
| MDB Mode       |     | ON  | ON  |     |
| ★ Reserved     |     |     |     | ON  |
|                |     |     |     | OFF |

★ Manufacture setting

### Interface Settings: 2(MDB)

| FUNCTION                         | SW1 | SW2 | SW3 | SW4 |
|----------------------------------|-----|-----|-----|-----|
| ★ Scaling Factor (SF) = 100      | ON  |     |     |     |
| Decimal Point Position (DPP) = 2 |     |     |     |     |
| Scaling Factor (SF) = 1          | OFF |     |     |     |
| Decimal Point Position (DPP) = 0 |     |     |     |     |
| Pulse Mode                       |     | ON  | OFF |     |
| ICT104U Mode                     |     | OFF | OFF |     |
| ICT104V Mode                     |     | OFF | ON  |     |
| ★ MDB Mode                       |     | ON  | ON  |     |
| ★ Reserved                       |     |     |     | ON  |
|                                  |     |     |     | OFF |

★ Manufacture setting