

V7P-CLP5

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill Ch\$ 1000, 2000, 5000, 10000, 20000 5bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ch\$ 1000	ON											
	Accept Ch\$ 1000	OFF											
★	Reject Ch\$ 2000		ON										
★	Accept Ch\$ 2000		OFF										
★	Reject Ch\$ 5000			ON									
★	Accept Ch\$ 5000			OFF									
★	Reject Ch\$ 10000				ON								
★	Accept Ch\$ 10000				OFF								
★	Reject Ch\$ 20000					ON							
★	Accept Ch\$ 20000					OFF							
	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / Ch\$ 1000								OFF	OFF			
	2 pulses / Ch\$ 1000								ON	OFF			
	4 pulses / Ch\$ 1000								OFF	ON			
	20 pulses / Ch\$ 1000								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7P-CLP5(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	MDB	Pulse
BV1	Ch\$ 1000	Ch\$ 1000	Ch\$ 1000	Ch\$ 1000
BV2	Ch\$ 2000	Ch\$ 2000	Ch\$ 2000	Ch\$ 2000
BV3	Ch\$ 5000	Ch\$ 5000	Ch\$ 5000	Ch\$ 5000
BV4	Ch\$ 10000	Ch\$ 10000	Ch\$ 10000	Ch\$ 10000
BV5	Ch\$ 20000	Ch\$ 20000	Ch\$ 20000	Ch\$ 20000

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON			
	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting