

V7P-IDR7

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill IDR 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject IDR 1000 & 2000	ON											
★	Accept IDR 1000 & 2000	OFF											
★	Reject IDR 5000 & 10000		ON										
★	Accept IDR 5000 & 10000		OFF										
★	Reject IDR 20000			ON									
★	Accept IDR 20000			OFF									
★	Reject IDR 50000			ON									
★	Accept IDR 50000			OFF									
★	Reject IDR 100000				ON								
★	Accept IDR 100000				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Harness Disable					ON							
★	Harness Enable					OFF							
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / IDR 1000								OFF	OFF			
★	5 pulses / IDR 1000								ON	OFF			
★	10 pulses / IDR 1000								OFF	ON			
★	25 pulses / IDR 1000								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

4.Calibrate card is needed.

V7P-IDR7(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	IDR 1000	IDR 1000	IDR 1000	IDR 1000
BV2	IDR 2000	IDR 2000	IDR 2000	IDR 2000
BV3	IDR 5000	IDR 5000	IDR 5000	IDR 5000
BV4	IDR 10000	IDR 10000	IDR 10000	IDR 10000
BV5	IDR 20000	IDR 20000	IDR 20000	IDR 20000
BV6	IDR 50000	IDR 50000	IDR 50000	IDR 50000
BV7	IDR 100000	IDR 100000	IDR 100000	IDR 100000

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting