

## V7P-INR6

### V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill Rs 10, 20, 50, 100, 200, 500 6bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Rs 10 & 20	ON											
★	Accept Rs 10 & 20	OFF											
★	Reject Rs 50		ON										
★	Accept Rs 50		OFF										
★	Reject Rs 100			ON									
★	Accept Rs 100			OFF									
★	Reject Rs 200			ON									
★	Accept Rs 200			OFF									
★	Reject Rs 500				ON								
★	Accept Rs 500				OFF								
★	Medium Security				ON								
★	High Security				OFF								
★	Harness Disable				ON								
★	Harness Enable				OFF								
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / Rs 10								OFF	OFF			
★	2 pulses / Rs 10								ON	OFF			
★	5 pulses / Rs 10								OFF	ON			
★	10 pulses / Rs 10								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

4.Calibrate card is needed.

## V7P-INR6(Pulse/ICT104V/ICT104U/MDB)

### Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1				
BV2	Rs 10	Rs 10	Rs 10	Rs 10
BV3	Rs 20	Rs 20	Rs 20	Rs 20
BV4	Rs 50	Rs 50	Rs 50	Rs 50
BV5	Rs 100	Rs 100	Rs 100	Rs 100
BV6	Rs 200	Rs 200	Rs 200	Rs 200
BV7	Rs 500	Rs 500	Rs 500	Rs 500

### Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting