

V7P-KRW4

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill KRW 1000, 5000, 10000, 50000 4bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject KRW 1000	ON											
	Accept KRW 1000	OFF											
★	Reject KRW 5000		ON										
	Accept KRW 5000		OFF										
★	Reject KRW 10000			ON									
	Accept KRW 10000			OFF									
★	Reject KRW 50000				ON								
	Accept KRW 50000				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Harness Disable					ON							
★	Harness Enable					OFF							
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
	Pulse Mode												
★	1 pulse / KRW 1000							OFF	OFF				
	5 pulses / KRW 1000							ON	OFF				
	10 pulses / KRW 1000							OFF	ON				
	20 pulses / KRW 1000							ON	ON				
★	Interface Timing Conversion	50ms LO / 50ms HI						OFF		OFF			
		60ms LO / 300ms HI						ON		OFF			
		30ms LO / 50ms HI						OFF		ON			
		150ms LO / 150ms HI						ON		ON			

★ Manufacture setting

Note :

1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

V7P-KRW4(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface	Pulse	MDB	ICT104V	ICT104U
BV1	KRW 1000	KRW 1000	KRW 1000	KRW 1000
BV2	KRW 5000	KRW 5000	KRW 5000	KRW 5000
BV3	KRW 10000	KRW 10000	KRW 10000	KRW 10000
BV4	KRW 50000	KRW 50000	KRW 50000	KRW 50000

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 10	ON			
	Decimal Point Position (DPP) = 1	OFF			
	Scaling Factor (SF) = 1				
	Decimal Point Position (DPP) = 0				
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting