

V7P-KWD4

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill KWD 0.25, 0.5, 1, 5 4bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject KWD 0.25	ON											
★ Accept KWD 0.25	OFF											
★ Reject KWD 0.5		ON										
★ Accept KWD 0.5		OFF										
★ Reject KWD 1			ON									
★ Accept KWD 1			OFF									
★ Reject KWD 5				ON								
★ Accept KWD 5				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ Pulse Mode												
★ 1 pulse / KWD 0.25									OFF	OFF		
★ 2 pulses / KWD 0.25									ON	OFF		
★ 4 pulses / KWD 0.25									OFF	ON		
★ 20 pulses / KWD 0.25									ON	ON		
★ Interface Timing Conversion											OFF	OFF
			50ms LO / 50ms HI								ON	OFF
			60ms LO / 300ms HI								OFF	ON
			30ms LO / 50ms HI								ON	ON
			150ms LO / 150ms HI								OFF	OFF

★ Manufacture setting

Note :

1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

V7P-KWD4(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface	Pulse	MDB	ICT104V	ICT104U
★ Bill value				
BV1	KWD 0.25	KWD 0.25	KWD 0.25	KWD 0.25
BV2	KWD 0.5	KWD 0.5	KWD 0.5	KWD 0.5
BV3	KWD 1	KWD 1	KWD 1	KWD 1
BV4	KWD 5	KWD 5	KWD 5	KWD 5

Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 1000	ON			
Decimal Point Position (DPP) = 3				
Scaling Factor (SF) = 100	OFF			
Decimal Point Position (DPP) = 2				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting