

V7P-PHP6

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill PHP 20, 50, 100, 200, 500, 1000 6bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject PHP 20	ON											
★	Accept PHP 20	OFF											
★	Reject PHP 50		ON										
★	Accept PHP 50		OFF										
★	Reject PHP 100			ON									
★	Accept PHP 100			OFF									
★	Reject PHP 200				ON								
★	Accept PHP 200				OFF								
★	Reject PHP 500 & 1000				ON								
★	Accept PHP 500 & 1000				OFF								
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / PHP 10								OFF	OFF			
★	5 pulses / PHP 10								ON	OFF			
★	10 pulses / PHP 10								OFF	ON			
★	20 pulses / PHP 10								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) Scaling Factor (SF) = 10, Decimal Point Position (DPP) = 1, Country CODE = 0063.

V7P-PHP6(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1	PHP 20	PHP 20	PHP 20	PHP 20
BV2	PHP 50	PHP 50	PHP 50	PHP 50
BV3	PHP 100	PHP 100	PHP 100	PHP 100
BV4	PHP 500	PHP 500	PHP 200	PHP 200
BV5	PHP 1000	PHP 1000	PHP 500	PHP 500
BV6	PHP 200	PHP 200	PHP 1000	PHP 1000

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Customized Mode (Note.4)				ON
★	Standard				OFF

★ Manufacture setting