

XBA mini-MUP8

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT)

Supported bill N\$ 20, 50, 100, 200 4bills.

USD\$ 1, 5, 10, 20 4bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject N\$ 20 & USD\$ 1	ON											
★ Accept N\$ 20 & USD\$ 1	OFF											
★ Reject N\$ 50 & USD\$ 5		ON										
★ Accept N\$ 50 & USD\$ 5		OFF										
★ Reject N\$ 100 & USD\$ 10			ON									
★ Accept N\$ 100 & USD\$ 10			OFF									
★ Reject N\$ 200 & USD\$ 20				ON								
★ Accept N\$ 200 & USD\$ 20				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ Reserved								ON				
★ Reserved								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ Reserved										ON		
★ Reserved										OFF		
★ Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
	60ms on / 300ms off										ON	OFF
	30ms on / 50ms off										OFF	ON
	150ms on / 150ms off										ON	ON

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Calibrate card

(3) Exchange Rate on USD to MXP is 1:10

XBA mini-MUP8(Pulse/MDB/JPSTD/ICT)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ 1 pulse / N\$ 10			OFF	OFF
2 pulses / N\$ 10			OFF	ON
5 pulses / N\$ 10			ON	OFF
10 pulses / N\$ 10			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT)

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
MDB Mode			OFF	OFF
JPSTD Mode			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD	ICT104U	ICT104V	Pulse	MDB
BV1	USD\$ 1				
BV2	N\$ 20				
BV3	N\$ 50 & USD\$ 5				
BV4	N\$ 100 & USD\$ 10				
BV5	N\$ 200 & USD\$ 20				

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
Other Mode		OFF		
★ MDB Mode			OFF	OFF
JPSTD Mode			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting