

A6-AUD5

A6 Option Switch Settings: 1

Supported bill \$A 5, 10, 20, 50, 100 5bills.

A6 dip-switch settings and functions:

	FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4		
★	Reject	\$A 5	ON													
	Accept	\$A 5	OFF													
★	Reject	\$A 10		ON												
	Accept	\$A 10		OFF												
★	Reject	\$A 20			ON											
	Accept	\$A 20			OFF											
★	Reject	\$A 50				ON										
	Accept	\$A 50				OFF										
★	Reject	\$A 100					ON									
	Accept	\$A 100					OFF									
★	High Acceptance (Note.3)							ON								
	High Security							OFF								
★	Harness Disable								ON							
	Harness Enable								OFF							
★	Inhibit Active High									ON						
	Inhibit Active Low									OFF						
★	1 pulse / \$A 5	1 pulse / \$A 5	(Note.4)								OFF	OFF				
	3 pulse / \$A 5	5 pulse / \$A 5	(Note.4)								ON	OFF				
★	5 pulse / \$A 5	10 pulse / \$A 5	(Note.4)								OFF	ON				
	6 pulse / \$A 5	20 pulse / \$A 5	(Note.4)								ON	ON				
★	Interface Timing Conversion		50ms LO / 50ms HI										OFF	OFF		
			60ms LO / 300ms HI										ON	OFF		
			30ms LO / 50ms HI										OFF	ON		
			150ms LO / 150ms HI										ON	ON		

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) High acceptance mode will increasing rate, however, it will reduce the security level of Bill Acceptor.

(4) Special pulse:When DIP-SW4 is ON,AUD 5=1 pulse,or 3 pulse,or 5 pulse,or 6 pulse.

Normal pulse:When DIP-SW4 is OFF,AUD 5=1 pulse,or 5 pulse,or 10 pulse,or 20 pulse.

A6-AUD5

A6 Light Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ICT002 Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Special pulse (Note 4)				ON
Normal pulse (Note 4)				OFF

★ Manufacture setting

Note.4. Special pulse:When DIP-SW4 is ON,AUD 5=1 pulse,or 3 pulse,or 5 pulse,or 6 pulse.

Normal pulse:When DIP-SW4 is OFF,AUD 5=1 pulse,or 5 pulse,or 10 pulse,or 20 pulse.

A6 Light Interface Settings: 2 (ICT002)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON		
★ ICT002 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT002
BV1	\$A 5	\$A 5
BV2	\$A 10	\$A 10
BV3	\$A 20	\$A 20
BV4	\$A 50	\$A 50
BV4	\$A 100	\$A 100