

# A6-USD2

## A6 Option Switch Settings: 1 (Special Pulse)

Supported bill US\$ 1, 5                      2 bills.

|   | FUNCTION               | SW1                  | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 |     |
|---|------------------------|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|
|   | Reject US\$ 1          | ON                   |     |     |     |     |     |     |     |     |
| ★ | Accept US\$ 1          | OFF                  |     |     |     |     |     |     |     |     |
|   | Reject US\$ 5          |                      |     |     |     |     |     |     |     | ON  |
| ★ | Accept US\$ 5          |                      |     |     |     |     |     |     |     | OFF |
| ★ | 1 pulse / one dollar   |                      |     | OFF | OFF |     |     |     |     |     |
|   | 2 pulses / one dollar  |                      |     | ON  | OFF |     |     |     |     |     |
|   | 4 pulses / one dollar  |                      |     | OFF | ON  |     |     |     |     |     |
|   | 20 pulses / one dollar |                      |     | ON  | ON  |     |     |     |     |     |
| ★ | Pulse Speed            | 50ms on / 50ms off   |     |     |     | OFF | OFF |     |     |     |
|   |                        | 60ms on / 300ms off  |     |     |     | ON  | OFF |     |     |     |
|   |                        | 30ms on / 50ms off   |     |     |     | OFF | ON  |     |     |     |
|   |                        | 150ms on / 150ms off |     |     |     | ON  | ON  |     |     |     |
|   | Harness Disable        |                      |     |     |     |     |     | ON  |     |     |
| ★ | Harness Enable         |                      |     |     |     |     |     | OFF |     |     |
|   | Inhibit Active High    |                      |     |     |     |     |     |     | ON  |     |
| ★ | Inhibit Active Low     |                      |     |     |     |     |     |     | OFF |     |

## Interface Settings: 2

|   | INTERFACE               | SW1 | SW2 | SW3 | SW4 |     |  |  |
|---|-------------------------|-----|-----|-----|-----|-----|--|--|
|   | Special Pulse (Note.2 ) | ON  |     |     |     |     |  |  |
| ★ | STD Pulse               | OFF |     |     |     |     |  |  |
|   | Reserved                |     |     |     |     | ON  |  |  |
| ★ | Reserved                |     |     |     |     | OFF |  |  |
|   | Reserved                |     |     |     |     | ON  |  |  |
| ★ | Reserved                |     |     |     |     | OFF |  |  |
|   | Reserved                |     |     |     |     | ON  |  |  |
| ★ | Reserved                |     |     |     |     | OFF |  |  |

◆ Factory configuration has all switches in the OFF position.

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

| (2) | SW2 Dip Switch 1 is OFF | SW2 Dip Switch 1 is ON |
|-----|-------------------------|------------------------|
|     | STD Pulse               | Special Pulse          |
|     | US\$ 1= 1 Pulse         | US\$ 1= 1 Pulse        |
|     | US\$ 5= 5 Pulses        | US\$ 5= 6 Pulses       |

