

A7/V7-ROL3

A7/V7 Option Switch Settings:1(Pulse/ccTalk)

Supported bill Lei 1, 5, 10 3bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Lei 1	ON											
★	Accept Lei 1	OFF											
★	Reject Lei 5		ON										
★	Accept Lei 5		OFF										
★	Reject Lei 10			ON									
★	Accept Lei 10			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved					ON							
★	Reserved					OFF							
★	Reserved						ON						
★	Reserved						OFF						
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / Lei 1									OFF	OFF		
★	2 pulse / Lei 1									ON	OFF		
★	5 pulse / Lei 1									OFF	ON		
★	20 pulse / Lei 1									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI								OFF		OFF	
		60ms LO / 300ms HI								ON		OFF	
		30ms LO / 50ms HI								OFF		ON	
		150ms LO / 150ms HI								ON		ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-ROL3(Pulse/ccTalk)

Interface Settings: 3(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ccTalk Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

Interface Settings: 3(ccTalk)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	ccTalk Interface		OFF		
▲	cctalk Parameters Restore Switch			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

▲ Put this switch to on and reset power will restore the cctalk address to its default value of 40,and the encryption key to its default value of 123456. This needs to be done after each White card Calibration.

Currency Assign Data

Interface Bill value	ccTalk	Pulse
BV1	Lei 1	Lei 1
BV2	Lei 5	Lei 5
BV3	Lei 10	Lei 10