

A7/V7-TJS5

A7/V7 Option Switch Settings : 1 Supported bill TJS 1, 3, 5, 10, 20 5bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject TJS 1	ON											
★	Accept TJS 1	OFF											
★	Reject TJS 3		ON										
★	Accept TJS 3		OFF										
★	Reject TJS 5			ON									
★	Accept TJS 5			OFF									
★	Reject TJS 10				ON								
★	Accept TJS 10				OFF								
★	Reject TJS 20				ON								
★	Accept TJS 20				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Harness Disable					ON							
★	Harness Enable					OFF							
★	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / TJS 1							OFF	OFF				
★	2 pulse / TJS 1							ON	OFF				
★	5 pulse / TJS 1							OFF	ON				
★	20 pulse / TJS 1							ON	ON				
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-TJS5

A7/V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

A7/V7 Interface Settings: 3 (RS232)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	RS232 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface (Note 1)		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON			
	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	OFF			
	Pulse Mode		ON		
★	MDB Interface (Note 1)		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

Note: (1) Please refer to the dip-switch #1 of internal dip-switch for MDB Decimal Point Setup.

(2)	Interface Bill value	Pulse	MDB
	BV1	TJS 1	TJS 1
	BV2	TJS 3	TJS 3
	BV3	TJS 5	TJS 5
	BV4	TJS 10	TJS 10
	BV5	TJS 20	TJS 20