

L70-IDR4

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill Rp 10000, 20000, 50000, 100000 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
1 Pulse / Rp 10000	OFF	OFF	OFF							
2 Pulse / Rp 10000	OFF	OFF	ON							
3 Pulse / Rp 10000	OFF	ON	OFF							
4 Pulse / Rp 10000	OFF	ON	ON							
5 Pulse / Rp 10000	ON	OFF	OFF							
10 Pulse / Rp 10000	ON	OFF	ON							
20 Pulse / Rp 10000	ON	ON	OFF							
100 Pulse / Rp 10000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
Inhibit level Active High				OFF						
Accept Rp 10000				ON						
Reject Rp 10000				OFF						
Accept Rp 20000				ON						
Reject Rp 20000				OFF						
Accept Rp 50000				ON						
Reject Rp 50000				OFF						
Accept Rp 100000				ON						
Reject Rp 100000				OFF						
High Security (Note.3)				ON						
High Acceptance				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(4) The function(credit divide by1000) is only used at standard MDB recycler mode

(5) i .Special MDB setting mode works for vending machine. It can't accept IDR 100,000 bill in this mode.

ii.The function(Normal credit/Credit divide) is disable when BA works at special MDB Setting Mode.

Appendix

L70-IDR4(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
Pulse Normal High	ON			
Pulse Normal Low	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ICT104U	ICT104V
BV1	Rp 10000	Rp 10000	Rp 10000	Rp 10000
BV2	Rp 20000	Rp 20000	Rp 20000	Rp 20000
BV3	Rp 50000	Rp 50000	Rp 50000	Rp 50000
BV4	Rp 100000	Rp 100000	Rp 100000	Rp 100000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
Normal credit	ON			
Credit divide by 1000(MDB only) (Note.4)	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Special MDB Setting(Base 5) (Note.5)				ON
Normal MDB Setting				OFF

★ Manufacture setting