

L70-VND7

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/MDB)

Supported bill VND 5000, 10000, 20000, 50000, 100000, 200000, 500000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / VND 5000 & 100000	OFF	OFF	OFF							
	2 Pulses / VND 5000 & 100000	OFF	OFF	ON							
	3 Pulses / VND 5000 & 100000	OFF	ON	OFF							
	4 Pulses / VND 5000 & 100000	OFF	ON	ON							
	5 Pulses / VND 5000 & 100000	ON	OFF	OFF							
	10 Pulses / VND 5000 & 100000	ON	OFF	ON							
	20 Pulses / VND 5000 & 100000	ON	ON	OFF							
	100 Pulses / VND 5000 & 100000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept VND 5000 (Note.3)				ON						
	Reject VND 5000 (Note.3)				OFF						
★	Accept VND 10000					ON					
	Reject VND 10000					OFF					
★	Accept VND 20000						ON				
	Reject VND 20000						OFF				
★	Accept VND 50000							ON			
	Reject VND 50000							OFF			
★	Accept VND 100000 & 200000 & 500000								ON		
	Reject VND 100000 & 200000 & 500000								OFF		

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

Note.3 Pulse Mode:

When Dip 6 is OFF,One Pulse per VND 10000.

When Dip 6 is ON ,One Pulse per VND 5000.

L70-VND7(Pulse/ICT106U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U	ICT104V
BV1	VND 5000	VND 5000	VND 5000	VND 5000
BV2	VND 10000	VND 10000	VND 10000	VND 10000
BV3	VND 20000	VND 20000	VND 20000	VND 20000
BV4	VND 50000	VND 50000	VND 50000	VND 50000
BV5	VND 100000	VND 100000	VND 100000	VND 100000
BV6	VND 200000	VND 200000	VND 200000	VND 200000
BV7	VND 500000	VND 500000	VND 500000	VND 500000

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT106U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting