

# L70-ZAR5

## L70/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0/V2.2)

Supported bill ZAR 10, 20, 50, 100, 200 5bills.

|   | FUNCTION                                  | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |  |  |  |  |  |
|---|-------------------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|--|--|--|--|--|
| ★ | 1 Pulse / ZAR 10                          | OFF | OFF | OFF |     |     |     |     |     |     |      |  |  |  |  |  |
|   | 2 Pulses / ZAR 10                         | OFF | OFF | ON  |     |     |     |     |     |     |      |  |  |  |  |  |
|   | 3 Pulses / ZAR 10                         | OFF | ON  | OFF |     |     |     |     |     |     |      |  |  |  |  |  |
|   | 4 Pulses / ZAR 10                         | OFF | ON  | ON  |     |     |     |     |     |     |      |  |  |  |  |  |
|   | 5 Pulses / ZAR 10                         | ON  | OFF | OFF |     |     |     |     |     |     |      |  |  |  |  |  |
|   | 10 Pulses / ZAR 10                        | ON  | OFF | ON  |     |     |     |     |     |     |      |  |  |  |  |  |
|   | 20 Pulses / ZAR 10                        | ON  | ON  | OFF |     |     |     |     |     |     |      |  |  |  |  |  |
|   | 100 Pulses / ZAR 10                       | ON  | ON  | ON  |     |     |     |     |     |     |      |  |  |  |  |  |
|   | Fast output Pulse<br>Lo= 50ms<br>Hi=100ms |     |     |     | ON  |     |     |     |     |     |      |  |  |  |  |  |
| ★ | Slow output Pulse<br>Lo= 50ms<br>Hi=300ms |     |     |     | OFF |     |     |     |     |     |      |  |  |  |  |  |
|   | Inhibit level Active Low                  |     |     |     |     | ON  |     |     |     |     |      |  |  |  |  |  |
| ★ | Inhibit level Active High                 |     |     |     |     | OFF |     |     |     |     |      |  |  |  |  |  |
| ★ | Accept ZAR 10                             |     |     |     |     |     |     | ON  |     |     |      |  |  |  |  |  |
|   | Reject ZAR 10                             |     |     |     |     |     |     | OFF |     |     |      |  |  |  |  |  |
| ★ | Accept ZAR 20                             |     |     |     |     |     |     | ON  |     |     |      |  |  |  |  |  |
|   | Reject ZAR 20                             |     |     |     |     |     |     | OFF |     |     |      |  |  |  |  |  |
| ★ | Accept ZAR 50                             |     |     |     |     |     |     |     | ON  |     |      |  |  |  |  |  |
|   | Reject ZAR 50                             |     |     |     |     |     |     |     | OFF |     |      |  |  |  |  |  |
| ★ | Accept ZAR 100                            |     |     |     |     |     |     |     |     | ON  |      |  |  |  |  |  |
|   | Reject ZAR 100                            |     |     |     |     |     |     |     |     | OFF |      |  |  |  |  |  |
| ★ | Accept ZAR 200                            |     |     |     |     |     |     |     |     |     | ON   |  |  |  |  |  |
|   | Reject ZAR 200                            |     |     |     |     |     |     |     |     |     | OFF  |  |  |  |  |  |

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse mode.

## L70-ZAR5(Pulse/RS232 A0/V2.2)

### DIP SWITCHES SETTING : 2(Pulse)

|   | FUNCTION          | SW1 | SW2 | SW3 | SW4 |
|---|-------------------|-----|-----|-----|-----|
| ★ | Pulse Normal High | ON  |     |     |     |
|   | Pulse Normal Low  | OFF |     |     |     |
| ★ | Pulse Mode        |     | ON  | OFF |     |
|   | RS232 A0 Mode     |     | ON  | ON  |     |
|   | V2.2 Mode         |     | OFF | ON  |     |
|   | Reserved          |     | OFF | OFF |     |
| ★ | Reserved          |     |     |     | ON  |
|   |                   |     |     |     | OFF |

★ Manufacture setting

### Currency Assign Data

| Interface<br>Bill value | Pulse  | RS232 A0 | V2.2   |
|-------------------------|--------|----------|--------|
| BV1                     | ZAR 10 |          | ZAR 10 |
| BV2                     | ZAR 20 |          | ZAR 20 |
| BV3                     | ZAR 50 |          | ZAR 50 |
| BV4                     | ZAR100 | ZAR 10   | ZAR100 |
| BV5                     | ZAR200 | ZAR 20   | ZAR200 |
| BV6                     |        | ZAR 50   |        |
| BV7                     |        | ZAR100   |        |
| BV8                     |        | ZAR200   |        |

### DIP SWITCHES SETTING : 2(RS232 A0)

|   | FUNCTION      | SW1 | SW2 | SW3 | SW4 |
|---|---------------|-----|-----|-----|-----|
| ★ | Reserved      | ON  |     |     |     |
|   |               | OFF |     |     |     |
|   | Pulse Mode    |     | ON  | OFF |     |
| ★ | RS232 A0 Mode |     | ON  | ON  |     |
|   | V2.2 Mode     |     | OFF | ON  |     |
|   | Reserved      |     | OFF | OFF |     |
| ★ | Reserved      |     |     |     | ON  |
|   |               |     |     |     | OFF |

★ Manufacture setting

### RS232 A0 INFORMATION

| BillType Data |              |
|---------------|--------------|
| Code          | Denomination |
| 1             | Reserved     |
| 2             | Reserved     |
| 3             | Reserved     |
| 4             | ZAR 10       |
| 5             | ZAR 20       |
| 6             | ZAR 50       |
| 7             | ZAR 100      |
| 8             | ZAR 200      |
| 9             | Reserved     |

### DIP SWITCHES SETTING : 2(V2.2)

|   | FUNCTION      | SW1 | SW2 | SW3 | SW4 |
|---|---------------|-----|-----|-----|-----|
| ★ | Reserved      | ON  |     |     |     |
|   |               | OFF |     |     |     |
|   | Pulse Mode    |     | ON  | OFF |     |
|   | RS232 A0 Mode |     | ON  | ON  |     |
| ★ | V2.2 Mode     |     | OFF | ON  |     |
|   | Reserved      |     | OFF | OFF |     |
| ★ | Reserved      |     |     |     | ON  |
|   |               |     |     |     | OFF |

★ Manufacture setting