

L70+/L70F-ZMW6

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/MDB/ICT104V/ICT104U)

Supported bill ZK 2, 5, 10, 20, 50, 100 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / ZK 1	OFF	OFF	OFF							
2 Pulse / ZK 1	OFF	OFF	ON							
3 Pulse / ZK 1	OFF	ON	OFF							
4 Pulse / ZK 1	OFF	ON	ON							
5 Pulse / ZK 1	ON	OFF	OFF							
10 Pulse / ZK 1	ON	OFF	ON							
20 Pulse / ZK 1	ON	ON	OFF							
100 Pulse / ZK 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept ZK 2						ON				
Reject ZK 2						OFF				
★ Accept ZK 5							ON			
Reject ZK 5							OFF			
★ Accept ZK 10								ON		
Reject ZK 10								OFF		
★ Accept ZK 20									ON	
Reject ZK 20									OFF	
★ Accept ZK 50 & 100										ON
Reject ZK 50 & 100										OFF

★ Manufacture setting

Note: Dip switches 1 to 5 are only used for pulse protocol.

L70+/L70F-ZMW6(Pulse/MDB/ICT104V/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
MDB Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
MDB Mode		ON	ON	
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
★ ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
★ MDB Mode		ON	ON	
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	ZK 2	ZK 2	ZK 2	ZK 2
BV2	ZK 5	ZK 5	ZK 5	ZK 5
BV3	ZK 10	ZK 10	ZK 10	ZK 10
BV4	ZK 20	ZK 20	ZK 20	ZK 20
BV5	ZK 50	ZK 50	ZK 50	ZK 50
BV6	ZK 100	ZK 100	ZK 100	ZK 100

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
MDB Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting