

L70/L70F-AZN5

L70 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccNet)

Supported bill MANAT 1, 5, 10, 20, 50 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MANAT 1	OFF	OFF	OFF							
	2 Pulse / MANAT 1	OFF	OFF	ON							
	3 Pulse / MANAT 1	OFF	ON	OFF							
	4 Pulse / MANAT 1	OFF	ON	ON							
	5 Pulse / MANAT 1	ON	OFF	OFF							
	10 Pulse / MANAT 1	ON	OFF	ON							
	20 Pulse / MANAT 1	ON	ON	OFF							
	100 Pulse / MANAT 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept MANAT 1				ON						
	Reject MANAT 1				OFF						
★	Accept MANAT 5				ON						
	Reject MANAT 5				OFF						
★	Accept MANAT 10				ON						
	Reject MANAT 10				OFF						
★	Accept MANAT 20				ON						
	Reject MANAT 20				OFF						
★	Accept MANAT 50				ON						
	Reject MANAT 50				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccNet
BV1	1	1	1
BV2	5	5	5
BV3	10	10	10
BV4	20	20	20
BV5	50	50	50

L70-AZN5(Pulse/ICT104U/ccNet)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Protocol Mode		ON	ON	
	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	ICT104U Protocol Mode		ON	ON	
	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccNet)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	9600 baud Rate	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Protocol Mode		ON	ON	
★	ccNet Mode		OFF	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting