

## L70+/L70F-BND3

### L70+/L70F DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill BND 1, 5, 10 3bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / BND 1	OFF	OFF	OFF							
2 Pulse / BND 1	OFF	OFF	ON							
3 Pulse / BND 1	OFF	ON	OFF							
4 Pulse / BND 1	OFF	ON	ON							
5 Pulse / BND 1	ON	OFF	OFF							
10 Pulse / BND 1	ON	OFF	ON							
20 Pulse / BND 1	ON	ON	OFF							
100 Pulse / BND 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept BND 1						ON				
Reject BND 1						OFF				
★ Accept BND 5							ON			
Reject BND 5							OFF			
★ Accept BND 10								ON		
Reject BND 10								OFF		
★ Reserve									ON	
Reserve									OFF	
★ Reserve										ON
Reserve										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) ICT104U supports Pulse signal via pulse credit cable.

## L70+/L70F-BND3(Pulse/ICT104U)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT104U Interface (Note.3)		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ ICT104U Interface (Note.3)		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	BND 1	BND 1
BV2	BND 5	BND 5
BV3	BND 10	BND 10