

L70/L70F-BOB5

L70&L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/Parallel A1)

Supported bill BOB 10, 20, 50, 100, 200 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / BOB 10	OFF	OFF	OFF							
	2 Pulses / BOB 10	OFF	OFF	ON							
	3 Pulses / BOB 10	OFF	ON	OFF							
	4 Pulses / BOB 10	OFF	ON	ON							
	5 Pulses / BOB 10	ON	OFF	OFF							
	10 Pulses / BOB 10	ON	OFF	ON							
	20 Pulses / BOB 10	ON	ON	OFF							
	100 Pulses / BOB 10	ON	ON	ON							
★	Fast output Pulse Lo= 50ms 										

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	ICT104U	Parallel A1
BV1	BOB 10	BOB 10	BOB 10
BV2	BOB 20	BOB 20	BOB 20
BV3	BOB 50	BOB 50	BOB 50

Interface Bill value	Pulse	ICT104U	Parallel A1
BV4	BOB 100	BOB 100	BOB 100
BV5	BOB 200	BOB 200	BOB 200

L70/L70F-BOB5/P5(Pulse/ICT104U/Parallel A1)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	ON	
	ICT104U Interface		OFF	OFF	
	Parallel A1 Mode		ON	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	ON	
★	ICT104U Interface		OFF	OFF	
	Parallel A1 Mode		ON	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A1)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	ON	
	ICT104U Interface		OFF	OFF	
★	Parallel A1 Mode		ON	OFF	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting