

L70/L70F-FJD4

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill FJD 5, 7, 10, 20, 4 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / FJD 1	OFF	OFF	OFF							
2 Pulses / FJD 1	OFF	OFF	ON							
3 Pulses / FJD 1	OFF	ON	OFF							
4 Pulses / FJD 1	OFF	ON	ON							
5 Pulses / FJD 1	ON	OFF	OFF							
10 Pulses / FJD 1	ON	OFF	ON							
20 Pulses / FJD 1	ON	ON	OFF							
100 Pulses / FJD 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept FJD 5						ON				
Reject FJD 5						OFF				
★ Accept FJD 7							ON			
Reject FJD 7							OFF			
★ Accept FJD 10								ON		
Reject FJD 10								OFF		
★ Accept FJD 20									ON	
Reject FJD 20									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	FJD 5	FJD 5	FJD 5	FJD 5
BV2	FJD 7	FJD 7	FJD 7	FJD 7
BV3	FJD 10	FJD 10	FJD 10	FJD 10
BV4	FJD 20	FJD 20	FJD 20	FJD 20

L70/L70F-FJD4(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting