

## L70+/L70F-HNL6

### L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0/Parallel A1)

Supported bill HNL 5, 10, 20, 50, 100, 500 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / HNL 5	OFF	OFF	OFF							
	2 Pulses / HNL 5	OFF	OFF	ON							
	3 Pulses / HNL 5	OFF	ON	OFF							
	4 Pulses / HNL 5	OFF	ON	ON							
	5 Pulses / HNL 5	ON	OFF	OFF							
	10 Pulses / HNL 5	ON	OFF	ON							
	20 Pulses / HNL 5	ON	ON	OFF							
	100 Pulses / HNL 5	ON	ON	ON							
	Fast output Pulse (Lo=50ms/ Hi=100ms)				ON						
★	Slow output (Lo=50ms/ Hi=300ms)				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept HNL 5 & 10						ON				
	Reject HNL 5 & 10						OFF				
★	Accept HNL 20						ON				
	Reject HNL 20						OFF				
★	Accept HNL 50							ON			
	Reject HNL 50							OFF			
★	Accept HNL 100								ON		
	Reject HNL 100								OFF		
★	Accept HNL 500									ON	
	Reject HNL 500									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.  
 (2) Dip switches 1 to 5 are only used for pulse protocol.  
 (3) Parallel A1 Protocol Reject HNL 5.  
 (4) RS232 A0 Protocol HNL 5 Code Denomination is 67h.

## L70+/L70F-HNL6/P5(Pulse/RS232 A0/Parallel A1)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	RS232 A0 Mode		OFF	OFF	
	Parallel A1 Mode		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	RS232 A0	Parallel A1
BV1	HNL 5	HNL 5	
BV2	HNL 10	HNL 10	HNL 10
BV3	HNL 20	HNL 20	HNL 20
BV4	HNL 50	HNL 50	HNL 50
BV5	HNL 100	HNL 100	HNL 100
BV6			
BV7	HNL 500	HNL 500	HNL 500

### DIP SWITCHES SETTING : 3(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	RS232 A0 Mode		OFF	OFF	
	Parallel A1 Mode		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

#### RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	HNL 10
2	HNL 20
3	HNL 50
4	HNL 100
5	Reserved
6	HNL 500
7	HNL 5
8	Reserved
9	Reserved

### DIP SWITCHES SETTING : 4(Parallel A1)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
	RS232 A0 Mode		OFF	OFF	
★	Parallel A1 Mode		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting