

L70+/L70F-IDR2

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill Rp 1000, 2000 2bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Rp 1000	OFF	OFF	OFF							
★ 2 Pulse / Rp 1000	OFF	OFF	ON							
3 Pulse / Rp 1000	OFF	ON	OFF							
4 Pulse / Rp 1000	OFF	ON	ON							
5 Pulse / Rp 1000	ON	OFF	OFF							
10 Pulse / Rp 1000	ON	OFF	ON							
20 Pulse / Rp 1000	ON	ON	OFF							
100 Pulse / Rp 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Rp 1000						ON				
Reject Rp 1000						OFF				
★ Accept Rp 2000							ON			
Reject Rp 2000							OFF			
★ Reserved								ON		
Reserved								OFF		
★ Reserved									ON	
Reserved									OFF	
★ High Acceptance (Note.3)										ON
High Security										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(4) The function(credit divide by1000) is only used at standard MDB recycler mode

(5) i .Special MDB setting mode works for vending machine. It can't accept IDR 100,000 bill in this mode.

ii.The function(Normal credit/Credit divide) is disable when BA works at special MDB Setting Mode.

Appendix

L70-IDR2(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ICT104U	ICT104V
BV1	Rp 1000	Rp 1000	Rp 1000	Rp 1000
BV2	Rp 2000	Rp 2000	Rp 2000	Rp 2000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Normal credit	ON			
Credit divide by 1000(MDB only) (Note.4)	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Special MDB Setting(Base 5) (Note.5)				ON
★ Normal MDB Setting				OFF

★ Manufacture setting