

L70+/L70F-MDL9

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/Special MDB)

Supported bill MDL 1, 5, 10, 20, 50, 100, 200, 500, 1000 9bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MDL 1 & 10	OFF	OFF	OFF							
	2 Pulse / MDL 1 & 10	OFF	OFF	ON							
	3 Pulse / MDL 1 & 10	OFF	ON	OFF							
	4 Pulse / MDL 1 & 10	OFF	ON	ON							
	5 Pulse / MDL 1 & 10	ON	OFF	OFF							
	10 Pulse / MDL 1 & 10	ON	OFF	ON							
	20 Pulse / MDL 1 & 10	ON	ON	OFF							
	100 Pulse / MDL 1 & 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept MDL 1 & 5	(Note.3)				ON					
	Reject MDL 1 & 5	(Note.3)				OFF					
★	Accept MDL 10 & 20					ON					
	Reject MDL 10 & 20					OFF					
★	Accept MDL 50						ON				
	Reject MDL 50						OFF				
★	Accept MDL 100 & 200							ON			
	Reject MDL 100 & 200							OFF			
★	Accept MDL 500 & 1000									ON	
	Reject MDL 500 & 1000									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) When SW1 Dip6 is ON

Pulse==>MDL 1=1 Pulse, MDL 5=5 Pulse,MDL 10=10 Pulse,MDL 20=20 Pulse,MDL 50=50 Pulse,
MDL 100=100 Pulse,MDL 200=200 Pulse,MDL 500=500 Pulse,MDL 1000=1000 Pulse
MDB ==>Reject MDL 500&1000.

When SW1 Dip6 is OFF

Pulse==>MDL 10=1 Pulse, MDL 20=2 Pulse,MDL 50=5 Pulse,MDL 100=10 Pulse,MDL 200=20 Pulse,
MDL 500=50 Pulse,MDL 1000=100 Pulse

MDB ==>Accept MDL 500&1000.

L70+/L70F-MDL9(Pulse/ICT104U/Special MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U		Pulse		MDB	
	Dip 6 is OFF	Dip 6 is ON	Dip 6 is OFF	Dip 6 is ON	Dip 6 is OFF	Dip 6 is ON
BV1		1		1	10	1
BV2		5		5	20	5
BV3	10	10	10	10	50	10
BV4	20	20	20	20	100	20
BV5	50	50	50	50	200	50
BV6	100	100	100	100	500	100
BV7	200	200	200	200	1000	200
BV8	500	500	500	500		
BV9	1000	1000	1000	1000		

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Note: 500 and 1000 not accept under MDB.