

L70+/L70F-NPR5

L70+/L70F-P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill NPR 5, 10, 20, 50, 100 5 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / NPR 5	OFF	OFF	OFF							
2 Pulse / NPR 5	OFF	OFF	ON							
3 Pulse / NPR 5	OFF	ON	OFF							
4 Pulse / NPR 5	OFF	ON	ON							
5 Pulse / NPR 5	ON	OFF	OFF							
10 Pulse / NPR 5	ON	OFF	ON							
20 Pulse / NPR 5	ON	ON	OFF							
100 Pulse / NPR 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept NPR 5						ON				
Reject NPR 5						OFF				
★ Accept NPR 10							ON			
Reject NPR 10							OFF			
★ Accept NPR 20								ON		
Reject NPR 20								OFF		
★ Accept NPR 50									ON	
Reject NPR 50									OFF	
★ Accept NPR 100										ON
Reject NPR 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+/L70F-NPR5(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	NPR 5	NPR 5	NPR 5	NPR 5
BV2	NPR 10	NPR 10	NPR 10	NPR 10
BV3	NPR 20	NPR 20	NPR 20	NPR 20
BV4	NPR 50	NPR 50	NPR 50	NPR 50
BV5	NPR 100	NPR 100	NPR 100	NPR 100

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting