

L70+/L70F-PHP4

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U/ICT104V/MDB)

Supported bill PHP 100, 200, 500, 1000 4 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / P. 100	OFF	OFF	OFF							
	2 Pulses / P. 100	OFF	OFF	ON							
	3 Pulses / P. 100	OFF	ON	OFF							
	4 Pulses / P. 100	OFF	ON	ON							
	5 Pulses / P. 100	ON	OFF	OFF							
	10 Pulses / P. 100	ON	OFF	ON							
	20 Pulses / P. 100	ON	ON	OFF							
	100 Pulses / P. 100	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept P. 100				ON						
	Reject P. 100				OFF						
★	Accept P. 200				ON						
	Reject P. 200				OFF						
★	Accept P. 500				ON						
	Reject P. 500				OFF						
★	Accept P. 1000				ON						
	Reject P. 1000				OFF						
★	Reserved				ON						
	Reserved				OFF						

★ Manufacture setting

Note.1 Please reset the bill acceptor after any changes on Dip switch.

Note.2 Dip Switch 1 to 5 are only for Pulse mode.

L70+/L70F-PHP4(Pulse/ICT106U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT106U	ICT104V
BV1	P. 100	P. 100	P. 100	P. 100
BV2	P. 200	P. 200	P. 200	P. 200
BV3	P. 500	P. 500	P. 500	P. 500
BV4	P. 1000	P. 1000	P. 1000	P. 1000

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT106U Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT106U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT106U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting