

L70+/L70F-PYG6

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill PYG 2000, 5000, 10000, 20000, 50000, 100000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / PYG 1000	OFF	OFF	OFF							
★ 2 Pulse / PYG 1000	OFF	OFF	ON							
★ 3 Pulse / PYG 1000	OFF	ON	OFF							
★ 4 Pulse / PYG 1000	OFF	ON	ON							
★ 5 Pulse / PYG 1000	ON	OFF	OFF							
★ 10 Pulse / PYG 1000	ON	OFF	ON							
★ 20 Pulse / PYG 1000	ON	ON	OFF							
★ 100 Pulse / PYG 1000	ON	ON	ON							
★ Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
★ Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept PYG 2000 & 5000				ON						
★ Reject PYG 2000 & 5000				OFF						
★ Accept PYG 10000				ON						
★ Reject PYG 10000				OFF						
★ Accept PYG 20000				ON						
★ Reject PYG 20000				OFF						
★ Accept PYG 50000				ON						
★ Reject PYG 50000				OFF						
★ Accept PYG 100000				ON						
★ Reject PYG 100000				OFF						

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+/L70F-PYG6(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ICT104U	ICT104V
BV1	PYG 2000	PYG 2000	PYG 2000	PYG 2000
BV2	PYG 5000	PYG 5000	PYG 5000	PYG 5000
BV3	PYG 10000	PYG 10000	PYG 10000	PYG 10000
BV4	PYG 20000	PYG 20000	PYG 20000	PYG 20000
BV5	PYG 50000	PYG 50000	PYG 50000	PYG 50000
BV6	PYG 100000	PYG 100000	PYG 100000	PYG 100000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 1000 Decimal Point Position (DPP) = 0	ON			
Scaling Factor (SF) = 1000 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting