

L70+/L70F-TZS5

L70+/L70F-P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB)

Supported bill TZS 500, 1000, 2000, 5000, 10000 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / TZS 500	OFF	OFF	OFF							
	2 Pulse / TZS 500	OFF	OFF	ON							
	3 Pulse / TZS 500	OFF	ON	OFF							
	4 Pulse / TZS 500	OFF	ON	ON							
	5 Pulse / TZS 500	ON	OFF	OFF							
	10 Pulse / TZS 500	ON	OFF	ON							
	20 Pulse / TZS 500	ON	ON	OFF							
	100 Pulse / TZS 500	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept TZS 500						ON				
	Reject TZS 500						OFF				
★	Accept TZS 1000							ON			
	Reject TZS 1000							OFF			
★	Accept TZS 2000								ON		
	Reject TZS 2000								OFF		
★	Accept TZS 5000									ON	
	Reject TZS 5000									OFF	
★	Accept TZS 10000										ON
	Reject TZS 10000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+/L70F-TZS5(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	MDB
BV1	TZS 500	TZS 500	TZS 500
BV2	TZS 1000	TZS 1000	TZS 1000
BV3	TZS 2000	TZS 2000	TZS 2000
BV4	TZS 5000	TZS 5000	TZS 5000
BV5	TZS 10000	TZS 10000	TZS 10000