

V7E+/LX7-BGN2

V7E+/LX7 Option Switch Settings: 1(Pulse/ICT104U/M.D.B)

Supported bill BGN 5, 10 2bills.

V7E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject BGN 5	ON											
★	Accept BGN 5	OFF											
★	Reject BGN 10		ON										
★	Accept BGN 10		OFF										
★	Reserved			ON									
★	Reserved			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved					ON							
★	Reserved					OFF							
★	Reserved						ON						
★	Reserved						OFF						
★	Pulse Mode	Other Mode											
★	Harness Disable	BA stops working when fishing					ON						
★	Harness Enable	Normal					OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / BGN 1								OFF	OFF			
★	2 pulses / BGN 1								ON	OFF			
★	4 pulses / BGN 1								OFF	ON			
★	20 pulses / BGN 1								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7E+/LX7-BGN2(Pulse/ICT104U/M.D.B)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	ICT104U Mode		OFF	ON	
★	Pulse Mode		ON	OFF	
	M.D.B Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT104U Mode		OFF	ON	
	Pulse Mode		ON	OFF	
	M.D.B Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U
BV1	BGN 5	BGN 5	BGN 5
BV2	BGN 10	BGN 10	BGN 10

DIP SWITCHES SETTING : 2(M.D.B)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	ICT104U Mode		OFF	ON	
★	Pulse Mode		ON	OFF	
	M.D.B Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

◆ Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.