

V7E/LX7-CLP4

V7E/LX7 Option Switch Settings: 1(Pulse/M.D.B)

Supported bill Ch\$ 1000, 2000, 5000, 10000 4bills.

V7E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ch\$ 1000	ON											
★	Accept Ch\$ 1000	OFF											
	Reject Ch\$ 2000		ON										
★	Accept Ch\$ 2000		OFF										
	Reject Ch\$ 5000			ON									
★	Accept Ch\$ 5000			OFF									
	Reject Ch\$ 10000				ON								
★	Accept Ch\$ 10000				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Disable sensor detect full cash box				ON								
★	Enable sensor detect full cash box				OFF								
	Harness Disable					ON							
★	Harness Enable					OFF							
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / Ch\$ 1000							OFF	OFF				
	2 pulse / Ch\$ 1000							ON	OFF				
	4 pulse / Ch\$ 1000							OFF	ON				
	20 pulse / Ch\$ 1000							ON	ON				
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E/LX7-CLP4(Pulse/M.D.B)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	Reserved		OFF	ON	
★	Pulse Mode		ON	OFF	
	M.D.B Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(M.D.B)

	FUNCTION	SW1	SW2	SW3	SW4
	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Reserved		OFF	ON	
	Pulse Mode		ON	OFF	
★	M.D.B Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

◆ Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	1,000	1,000
BV2	2,000	2,000
BV3	5,000	5,000
BV4	10,000	10,000