

V7E/LX7-EUR3

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT002U/MDB)

Supported bill € 5, 10, 20 3bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject € 5	ON											
★ Accept € 5	OFF											
★ Reject € 10		ON										
★ Accept € 10		OFF										
★ Reject € 20			ON									
★ Accept € 20			OFF									
Reject € 5(2002)&10(2002)				ON								
★ Accept Normal				OFF								
★ Reject € 20(2002)				ON								
★ Accept Normal				OFF								
★ Reserved					ON							
★ Reserved					OFF							
Pulse Mode	Other Mode											
★ Harness Disable	BA stops working when fishing					ON						
★ Harness Enable	Normal					OFF						
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / € 5								OFF	OFF			
★ 5 pulses / € 5								ON	OFF			
★ 10 pulses / € 5								OFF	ON			
★ 20 pulses / € 5								ON	ON			
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) BV1=€ 5 、 BV2=€ 10 、 BV3=€ 20.

V7E/LX7-EUR3(Pulse/ICT104V/ICT002U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT002U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	Pulse	ICT104V	ICT002U	MDB
BV1	€ 5	€ 5	€ 5	€ 5
BV2	€ 10	€ 10	€ 10	€ 10
BV3	€ 20	€ 20	€ 20	€ 20

Interface Settings: 2(ICT002U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Not Used	ON			
Not Used	OFF			
Pulse Mode		ON	OFF	
★ ICT002U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Not Used	ON			
Not Used	OFF			
Pulse Mode		ON	OFF	
★ ICT002U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT002U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting