

V7E/LX7-MNT5

V7E/LX7 Option Switch Settings: 1(Pulse/M.D.B)

Supported bill MNT 100, 500, 1000, 5000, 10000 5bills.

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MNT 100	ON											
★	Accept MNT 100	OFF											
	Reject MNT 500		ON										
★	Accept MNT 500		OFF										
	Reject MNT 1000			ON									
★	Accept MNT 1000			OFF									
	Reject MNT 5000				ON								
★	Accept MNT 5000				OFF								
	Reject MNT 10000					ON							
★	Accept MNT 10000					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing						ON					
★	Harness Enable	Normal						OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / MNT 100									OFF	OFF		
	2 pulse / MNT 100									ON	OFF		
	4 pulse / MNT 100									OFF	ON		
	20 pulse / MNT 100									ON	ON		
★	Pulse Speed	50ms HI / 50ms LO										OFF	OFF
		60ms HI / 300ms LO										ON	OFF
		30ms HI / 50ms LO										OFF	ON
		150ms HI / 150ms LO										ON	ON

★ Manufacture setting

◆ Note : (1) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

V7E/LX7-MNT5(Pulse/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	M.D.B Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	M.D.B Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse
BV1	MNT 100	MNT 100
BV2	MNT 500	MNT 500
BV3	MNT 1000	MNT 1000
BV4	MNT 5000	MNT 5000
BV5	MNT 10000	MNT 10000