

## BAM3

### P70/P2/P5 DIP SWITCHES SETTING : 1(Pulse/MDB)

Supported bill MARAKA 10, 20, 50 3bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / MARAKA 10	OFF	OFF	OFF							
2 Pulse / MARAKA 10	OFF	OFF	ON							
3 Pulse / MARAKA 10	OFF	ON	OFF							
4 Pulse / MARAKA 10	OFF	ON	ON							
5 Pulse / MARAKA 10	ON	OFF	OFF							
10 Pulse / MARAKA 10	ON	OFF	ON							
20 Pulse / MARAKA 10	ON	ON	OFF							
100 Pulse / MARAKA 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept MARAKA 10						ON				
Reject MARAKA 10						OFF				
★ Accept MARAKA 20							ON			
Reject MARAKA 20							OFF			
★ Accept MARAKA 50								ON		
Reject MARAKA 50								OFF		
★ Reserved									ON	
Reserved									OFF	
★ Reserved										ON
Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.  
(2) Dip switches 1 to 5 are only used for pulse protocol.

## P70-BAM3(Pulse/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
MDB Interface		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.  
(2) Dip switches 1 & 3 are only used for pulse protocol.

### DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
★ MDB Interface		OFF		
Reserved			ON	
★ Reserved			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	MARAKA 10	MARAKA 10
BV2	MARAKA 20	MARAKA 20
BV3	MARAKA 50	MARAKA 50