

COP6

P70/P5 DIP SWITCHES SETTING : 1(Parallel A1 Protocol)

Supported bill Col\$ 1000, 2000, 5000, 10000, 20000, 50000
6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
HOLD	OFF	OFF	OFF							
	OFF	OFF	ON							
	OFF	ON	OFF							
	OFF	ON	ON							
	ON	OFF	OFF							
	ON	OFF	ON							
	ON	ON	OFF							
	ON	ON	ON							
				ON						
				OFF						
★ Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept Col\$ 1000 & 2000						ON				
Reject Col\$ 1000 & 2000						OFF				
★ Accept Col\$ 5000							ON			
Reject Col\$ 5000							OFF			
★ Accept Col\$ 10000								ON		
Reject Col\$ 10000								OFF		
★ Accept Col\$ 20000									ON	
Reject Col\$ 20000									OFF	
★ Accept Col\$ 50000										ON
Reject Col\$ 50000										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
	OFF			
★ Parallel A1 Protocol		ON		
Hold		OFF		
Reserved			ON	
			OFF	
Ignore Sensor Problem(Note 1)				ON
★ Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)