

# P70-CRC5

## P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill Co\$ 1000, 2000, 5000, 10000, 20000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Co\$ 1000	OFF	OFF	OFF							
2 Pulse / Co\$ 1000	OFF	OFF	ON							
3 Pulse / Co\$ 1000	OFF	ON	OFF							
4 Pulse / Co\$ 1000	OFF	ON	ON							
5 Pulse / Co\$ 1000	ON	OFF	OFF							
10 Pulse / Co\$ 1000	ON	OFF	ON							
20 Pulse / Co\$ 1000	ON	ON	OFF							
100 Pulse / Co\$ 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Co\$ 1000						ON				
Reject Co\$ 1000						OFF				
★ Accept Co\$ 2000							ON			
Reject Co\$ 2000							OFF			
★ Accept Co\$ 5000								ON		
Reject Co\$ 5000								OFF		
★ Accept Co\$ 10000									ON	
Reject Co\$ 10000									OFF	
★ Accept Co\$ 20000										ON
Reject Co\$ 20000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT104U Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	1000	1000
BV2	2000	2000
BV3	5000	5000
BV4	10000	10000
BV5	20000	20000