



GEL7

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Lari 1, 2, 5, 10, 20, 50, 100 7bills.

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ 1 Pulse / Lari 1 | OFF | OFF | OFF | | | | | | | |
| 2 Pulse / Lari 1 | OFF | OFF | ON | | | | | | | |
| 3 Pulse / Lari 1 | OFF | ON | OFF | | | | | | | |
| 4 Pulse / Lari 1 | OFF | ON | ON | | | | | | | |
| 5 Pulse / Lari 1 | ON | OFF | OFF | | | | | | | |
| 10 Pulse / Lari 1 | ON | OFF | ON | | | | | | | |
| 20 Pulse / Lari 1 | ON | ON | OFF | | | | | | | |
| 100 Pulse / Lari 1 | ON | ON | ON | | | | | | | |
| Fast output Pulse <small>Lo= 50ms Hi=100ms</small> | | | | ON | | | | | | |
| ★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small> | | | | OFF | | | | | | |
| Inhibit level Active Low | | | | ON | | | | | | |
| ★ Inhibit level Active High | | | | OFF | | | | | | |
| ★ Accept Lari 1 & 2 | | | | ON | | | | | | |
| ★ Reject Lari 1 & 2 | | | | OFF | | | | | | |
| ★ Accept Lari 5 & 10 | | | | ON | | | | | | |
| ★ Reject Lari 5 & 10 | | | | OFF | | | | | | |
| ★ Accept Lari 20 | | | | ON | | | | | | |
| ★ Reject Lari 20 | | | | OFF | | | | | | |
| ★ Accept Lari 50 | | | | ON | | | | | | |
| ★ Reject Lari 50 | | | | OFF | | | | | | |
| ★ Accept Lari 100 | | | | ON | | | | | | |
| ★ Reject Lari 100 | | | | OFF | | | | | | |

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|-----------------------|-----|-----|-----|-----|
| ★ Pulse Normal High | ON | | | |
| Pulse Normal Low | OFF | | | |
| ★ Pulse Protocol | | ON | | |
| ICT Protocol | | OFF | | |
| ★ Harness Disable | | | ON | |
| ★ Harness Enable | | | OFF | |
| ★ Manufacture Default | | | | ON |
| ★ System Default | | | | OFF |

★ Manufacture setting