



# GEL7

## P70/P5 DIP SWITCHES SETTING : 1(Pulse/ MDB)

Supported bill Lari 1, 2, 5, 10, 20, 50, 100 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Lari 1	OFF	OFF	OFF								
	2 Pulse / Lari 1	OFF	OFF	ON								
	3 Pulse / Lari 1	OFF	ON	OFF								
	4 Pulse / Lari 1	OFF	ON	ON								
	5 Pulse / Lari 1	ON	OFF	OFF								
	10 Pulse / Lari 1	ON	OFF	ON								
	20 Pulse / Lari 1	ON	ON	OFF								
	100 Pulse / Lari 1	ON	ON	ON								
	Fast output Pulse Lo= 50ms Hi=100ms											ON
★	Slow output Pulse Lo= 50ms Hi=300ms											OFF
	Inhibit level Active Low				ON							
★	Inhibit level Active High				OFF							
★	Accept Lari 1 & 2						ON					
	Reject Lari 1 & 2						OFF					
★	Accept Lari 5							ON				
	Reject Lari 5							OFF				
★	Accept Lari 20								ON			
	Reject Lari 20								OFF			
★	Accept Lari 50									ON		
	Reject Lari 50									OFF		
★	Accept Lari 100										ON	
	Reject Lari 100										OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.  
(2) Dip switches 1 & 3 are only used for pulse protocol.

## DIP SWITCHES SETTING : 3(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting