

# P70-GTQ6

## P70/P2/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill GTQ 1, 5, 10, 20, 50, 100 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / GTQ 1	OFF	OFF	OFF							
2 Pulse / GTQ 1	OFF	OFF	ON							
3 Pulse / GTQ 1	OFF	ON	OFF							
4 Pulse / GTQ 1	OFF	ON	ON							
5 Pulse / GTQ 1	ON	OFF	OFF							
10 Pulse / GTQ 1	ON	OFF	ON							
20 Pulse / GTQ 1	ON	ON	OFF							
100 Pulse / GTQ 1	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept GTQ 1						ON				
Reject GTQ 1						OFF				
★ Accept GTQ 5 & 10							ON			
Reject GTQ 5 & 10							OFF			
★ Accept GTQ 20								ON		
Reject GTQ 20								OFF		
★ Accept GTQ 50									ON	
Reject GTQ 50									OFF	
★ Accept GTQ 100										ON
Reject GTQ 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 3 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2

## Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Interface Bill value	ICT	Pulse
BV1	GTQ 1	GTQ 1
BV2	GTQ 5	GTQ 5
BV3	GTQ 10	GTQ 10
BV4	GTQ 20	GTQ 20
BV5	GTQ 50	GTQ 50
BV6	GTQ 100	GTQ 100