

# MYR6

## P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill M\$ 1, 5, 10, 20, 50, 100 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / M\$ 1	OFF	OFF	OFF							
2 Pulse / M\$ 1	OFF	OFF	ON							
3 Pulse / M\$ 1	OFF	ON	OFF							
4 Pulse / M\$ 1	OFF	ON	ON							
5 Pulse / M\$ 1	ON	OFF	OFF							
10 Pulse / M\$ 1	ON	OFF	ON							
20 Pulse / M\$ 1	ON	ON	OFF							
100 Pulse / M\$ 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept M\$ 1						ON				
Reject M\$ 1						OFF				
★ Accept M\$ 5							ON			
Reject M\$ 5							OFF			
★ Accept M\$ 10								ON		
Reject M\$ 10								OFF		
★ Accept M\$ 20									ON	
Reject M\$ 20									OFF	
★ Accept M\$ 50 & 100										ON
Reject M\$ 50 & 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	1	1
BV2	2	2
BV3	5	5
BV4	10	10
BV5	50	50
BV6	100	100
BV7	20	20